

Cabinet Wizard

170 Cabinet Tester



Cabinets
Controllers
Signals
Signs
Software
Specialty

Overview

McCain's Cabinet Wizard is a simple and effective tool for testing 170 cabinet wiring. The Wizard provides manufacturing with a point-to-point test to verify wire harnessing. In the field, it aids contractors to ensure that they have made the correct termination (i.e. detector loops/signal heads/peds, preempts) and allows the technician to flash out the intersection, all without having the controller present in the cabinet.

Benefits

- Simple and effective means to test cabinet wiring
- Compact and easily portable
- Allows technicians to flash out an intersection
- Valuable troubleshooting tool

Standard Features

- Tests each load switch input and cabinet output
- Tests each I and J file field input and output to C1 or detect test panel
- Tests cabinet switches and CMU wiring
- Tests FTR's, IR and LR in an operating cabinet
- Test C1 to C4 and C5 harnesses
- Tests "Flash Sense" and "Stop Time" wiring
- Watch Dog Timer circuit
- High output audible continuity tester
- Input file switches (56)
- Controller output LEDs (54, including AUX file)
- On/Off/Momentary test switches (54)

Compatibility

The Wizard is compatible with the following cabinets:

- 332
- 333
- 336A and 336S

General Specifications

Dimensions:	18"W x 14" H x 6" D
Enclosure:	High impact ABS plastic luggage style case
Power:	120 VAC, 1 AMP
Environment:	Operating Temperature: +20° C to +74° C Humidity: 0 to 95% (non-condensing)
Shipping Weight:	19 lbs

2365 OAK RIDGE WAY // VISTA, CALIFORNIA 92081 // USA // WWW.MCCAIN-INC.COM

© 2009 McCain Inc. Updated 01/15/09. McCain reserves the right to change product specifications without notice.
For the most up-to-date information, please contact McCain.


www.mccain-inc.com